

# Product data sheet

## **NOT 220 AP \***



Emergency exit system emergency push button for mains voltage shut-off in the case of an emergency or during maintenance work, surface-mounted installation

### **AREAS OF APPLICATION**

- Mains voltage shut-off in the case of an emergency and during maintenance work
- Indirect release of GEZE emergency exit system door control units
- Opening of automatic doors in case of an emergency
- Surface-mounted installation for simple installation without a lot of effort
- Outdoors thanks to high IP rating

**PRODUCT FEATURES**

- LED lighting for better visibility, even in the dark
- Re-usable cover that protects against dust and dirt
- Contact system consists of one normally closed contact and one normally opened contact
- A second normally closed contact is available as an accessory
- Robust plastic housing protects the emergency push button reliably from mechanical effects

**TECHNICAL DATA**

Productname	NOT 220 AP *
Dimensions	94 x 94 x 122 mm
Supply voltage	24 V DC
Current consumption	17 mA
Type of installation	Surface-mounted installation
Service temperature	-10 - 50 °C

**VARIANTS / ORDER INFO**

Designation	Description	Ident-No.	Colour	Dimensions	Operating voltage
NOT 220 AP emergency stop switch, IP65 *	in plastic casing IP65 / 94 x 94 x 122 mm / with emergency exit sign arrow downwards / Operating voltage: 24 V DC / Contact rating: 3A, 250 V / 1 normally closed contact	076777	grey	94 x 94 x 122 mm	24 V DC

\* The products designated above may vary in form, type, characteristics, function, or availability depending on the country. Please get in touch with your GEZE contact person if you have any questions.